

**Amendments to the Claims:**

This listing of claims will replace all prior versions, and listings, of claims in the application:

**Listing of Claims:**

1. (Original) An apparatus for performing an initial symbol synchronization and detection operation in an OFDM (Orthogonal Frequency Division Multiplexing) receiver, the OFDM receiver including a correlator for making a correlation between a currently received signal and a previously received signal and outputting a result of the correlation, a sliding integrator for accumulating output signals of the correlator during a set guard interval and outputting a result of the accumulation, and a symbol integrator for accumulating output signals of the sliding integrator and outputting a result of the accumulation, said apparatus comprising:

a maximum-value detector for outputting a maximum-value detection signal when detecting a maximum value of accumulated correlation values from one of the integrators, and for selectively outputting a maximum value of accumulated correlation values from the other integrator;

a maximum-value position detector for outputting a count value currently counted by an internal counter as information associated with maximum-value position detection in response to the maximum-value detection signal; and

a guard-interval-mode discrimination unit for periodically comparing the count value outputted from the maximum-value position detector and a previous count value, producing a difference value between maximum-value positions, accumulating difference values during a predetermined time, producing an average value of the difference values, comparing the average value with a predetermined guard-interval discrimination parameter, and discriminating a guard interval mode and an FFT (Fast Fourier Transform) mode according to a result of the comparison.

2. (Original) The apparatus as set forth in claim 1, further comprising:

a counting period/length controller for adjusting a counting period of the maximum-value position detector and data lengths associated with the correlator and

the integrators in response to the discriminated FFT mode and guard interval mode;  
and

a useful-symbol start-point detector for adding a value of discriminated guard interval length to the count value outputted from the maximum-value position detector so that a start point of a useful symbol is detected.

3. (Currently Amended) The apparatus as set forth in claim 1, [[or 2,]] wherein data lengths associated with the correlator and the sliding integrator are set so that the correlator and the sliding integrator correspond to length of 2048 samples and length of 64 samples in an initial guard-interval discrimination mode, respectively, and wherein a counting period of the internal counter of the maximum-value position detector is set so that the internal counter of the maximum-value position detector periodically carries out a counting operation every 2048 samples.

4. (Currently Amended) The apparatus as set forth in claim 1, [[or 2,]] wherein the maximum-value detector allows a maximum-value position to be detected on the basis of a pre-arriving path in a form of accumulated correlation values for an SFN (Single Frequency Network).

5. (Original) An apparatus for performing an initial symbol synchronization and detection operation in an OFDM (Orthogonal Frequency Division Multiplexing) receiver, the OFDM receiver including a correlator for making a correlation between a currently received signal and a previously received signal of a previous symbol duration and outputting a result of the correlation, and sliding integrators, symbol integrators and maximum-value detectors outputting maximum values sequentially coupled to the correlator and associated with guard interval modes (1/32, 1/16, 1/8 and 1/4) so that types of guard intervals for an OFDM signal are discriminated, said apparatus comprising:

maximum-value position detectors for outputting count values currently counted by internal counters as information associated with maximum-value position detection in response to maximum-value detection signals from the maximum-value detectors arranged on guard interval paths; and

a guard-interval-mode discrimination unit for comparing a ratio of first and second largest values among the maximum values outputted from the maximum-value position detectors arranged on the guard interval paths with a threshold value, discriminating an FFT (Fast Fourier Transform) mode, and determining that a guard interval mode corresponding to a guard interval path that outputs the first largest value is valid.

6. (Original) The apparatus as set forth in claim 5, further comprising:

a useful-symbol start-point detector for adding a value of discriminated guard interval length to a count value outputted from a maximum-value position detector so that a start point of a useful symbol is detected.

7. (Original) A method for performing an initial symbol synchronization and detection operation so that a guard interval and useful data duration are discriminated from a modulated signal based on OFDM (Orthogonal Frequency Division Multiplexing) and an FFT (Fast Fourier Transform) operation is carried out, said method comprising the steps of:

detecting a position in which an output value of a sliding integrator is maximal from a path of an observation guard interval selected from a plurality of guard intervals;

comparing a value of the position in which the output value of the sliding integrator is maximal with a previous maximum-value position every counting period, producing a difference value between maximum-value positions, accumulating difference values during a predetermined time, producing an average value of the difference values, comparing the average value with a predetermined guard-interval discrimination parameter for the observation guard interval, and discriminating a guard interval mode and an FFT (Fast Fourier Transform) mode according to a result of the comparison; and

detecting a position in which an accumulated correlation value is maximal from a path of a discriminated guard interval, adding a value of discriminated guard interval length to a value of the detected position to produce an addition value, and outputting the addition value as information associated with a start point of a useful symbol.

8. (Original) The method as set forth in claim 7, further comprising the step of:

variably setting the counting period according to the discriminated guard interval mode.

9. (Currently Amended) The method as set forth in claim 7, [[or 8,]] wherein the observation guard interval path is a path of a guard interval corresponding to 1/32 of the useful data duration.

10. (Original) A method for performing an initial symbol synchronization and detection operation so that a guard interval and useful data duration are discriminated from a modulated signal based on OFDM (Orthogonal Frequency Division Multiplexing) and an FFT (Fast Fourier Transform) operation is carried out, said method comprising the steps of:

detecting positions in which accumulated correlation values are maximum during a symbol period from a plurality of guard interval paths and detecting maximum values from the accumulated correlation values;

comparing a ratio of first and second largest values from the detected maximum values with a preset threshold value, discriminating an FFT (Fast Fourier Transform) mode, and determining that a guard interval mode corresponding to a guard interval path that outputs the first largest value is valid; and

detecting a position in which an accumulated correlation value is maximal from a path of a discriminated guard interval, adding a value of discriminated guard interval length to a value of the detected position to produce an addition value, and outputting the addition value as information associated with a start point of a useful symbol.

11. (New) The apparatus as set forth in claim 2, wherein data lengths associated with the correlator and the sliding integrator are set so that the correlator and the sliding integrator correspond to length of 2048 samples and length of 64 samples in an initial guard-interval discrimination mode, respectively, and wherein a counting period of the internal counter of the maximum-value position detector is

set so that the internal counter of the maximum-value position detector periodically carries out a counting operation every 2048 samples.

12. (New) The apparatus as set forth in claim 2, wherein the maximum-value detector allows a maximum-value position to be detected on the basis of a pre-arriving path in a form of accumulated correlation values for an SFN (Single Frequency Network).

13. (New) The method as set forth in claim 8, wherein the observation guard interval path is a path of a guard interval corresponding to  $1/32$  of the useful data duration.